

## SENSOR AND SURVEILLANCE SYSTEMS | CONTROLLERS



### CLT-1000 AND CLT-1000R DIGITAL CONTROLLERS



The CLT digital interface tabletop controllers are designed to access and control all functions of Moog Pan and Tilt Positioners through RS232, RS422 or RS485 serial digital control. Both controllers are designed specifically to control the GeminEye line of positioners, but also can control Moog serial digital RS232/ RS422/ RS485 based positioners for less complex and lower cost applications.



# CLT-1000 AND CLT-1000R DIGITAL CONTROLLERS

## PERFORMANCE

Features	Model CLT-1000	Model CLT-1000R
Joystick	Proportional joystick with high-speed or precision control of pan and tilt movement	
Display	20 character by-line LCD screen	
Presets	Control and program of presets and tours	
Communication interface	RS232/422/485 serial data interface	
Power	9-32VDC power input (120VAC wall transformer included)	
Camera integration	Moog GeminEye system fully integrated (contact factory for other sensor integrations)	
Configuration	Configurable through LCD menu	
Chassis	Polycarbonate	Aluminum
Physical I/O connections	Input power (DC barrel plug), RS-422/485 (phoenix style connector), RS-232 (DB-9 connector), Alarms (phoenix style connector)	All inputs and outputs carried by a single MIL-SPEC connector



3650 Woodhead Drive Northbrook, IL, USA 60062-1895  
 +1.847.498.0700 Fax: +1.847.498.1258  
 s3insidesales@moog.com  
 www.moogS3.com



Moog Space and Defense



@MoogSDG



@MoogSDG



@MoogSDG



@MoogInc

This product is regulated by the U.S. Export Administration Regulations  
 15 CFR Parts 730-774, ECCN EAR99, export, disclosure or transfer contrary  
 to U.S. law is prohibited, purposes. Diversion contrary to US law is prohibited.

© 2021 Moog, Inc. All rights reserved.  
 Product and company names listed are trademarks or trade names of their respective companies.